

YEARS IN A ROW



brother

1

Colour wireless LED printer

im.

HL-L3230CDW



Colour wireless LED printer

The HL-L3230CDW is the ideal colour printer for businesses wanting to save time and money. With quick time saving features such as automatic 2-sided (duplex) printing and the large 250 sheet paper capacity, this printer is a real asset to any office. It also offers both wired and wireless connectivity, with the added benefit of printing on the go from your mobile or tablet.



HL-L3230CDW

Key Features:

- Fast print speeds of up to 24 pages⁶ per minute
- Large paper capacity of 250 sheets
- Automatic 2-sided (duplex) printing
- Wired and wireless connectivity
- Easily print from your mobile or tablet
- 256MB memory
- Up to 1,000 pages¹ in-box toners



Productivity gains for your business

Watch your business productivity soar with up to 24PPM print speeds⁶ with this easy to set up and easy to use printer.



Wireless and mobile connectivity

Loads of connectivity options for your business. Print wirelessly from your desktop, laptop, smartphone or tablet for mobile device printing.



Best value - get business features at low running costs

With high-yield toners available (up to 2,500 pages¹ BK and 2,300 pages¹ CMY), your business can now benefit from super low running costs with high quality 2400dpi printing, ensuring you get maximum value from an economical device.



Designed to go the distance

Built to perform for longer, the HL-L3230CDW been designed with you in mind. Made from robust and hard wearing materials and supported by outstanding service as standard, Brother's award winning⁸ reliability allows you to deliver uncompromised performance at all times.

		Paper Handling	
Technology	Electrophotographic LED	Paper Input	Standard Tray - 250 sheets Manual feed slot - 1 sheet
Processor	Cortex-A9 800MHz Sub: ARM946 133MHz	Paper Output	150 sheets Face Down (80g/m2) 1 sheet face-up (straight paper path)
Memory	256MB	Media Type & Weights	Plain & Recycled paper
Wired Network	Ethernet 10Base-T/100Base-TX	Standard Tray	(between 60 - 163g/m2)
Wireless Network	IEEE 802.11b/g/n	Media Sizes Standard Tray Media Type & Weights 2-sided	A4, Letter, A5, A5 (Long Edge), A6, Executive Plain & Recycled paper
Control Panel	1 Line LCD	(duplex) Print	(between 60 - 163g/m2)
Local Interface	Hi-Speed USB 2.0	Media Sizes 2-sided (duplex) Print	A4
Mobile Print Print	Print from your mobile devices to your Brother printer	Envelope & Label Printing	Yes, from the manual feed slot: support for 1 envelope / sheet
Print Speed (A4)	Up to 24PPM ⁶ Colour & Monochrome	Media Type & Weights	Plain, Recycled, Bond, Label, Envelope paper
Print Speed 2-sided (duplex) (A4)	Up to 6 sides per minute Colour & Monochrome	Manual feed slot Media Sizes Manual feed slot	(between 60 - 163g/m2) Width 76.2 to 216 mm
Resolution	2,400 dpi (600 x 2400)		Length 116 to 355.6 mm Envelope; COM-10, DL, C5, Monarch
Quiet Mode	A mode to reduce the printing noise by reducing the		
	print speed	Mobile Connectivity	
FPOT (First Print Out Time)	Less than 15.5 seconds from ready mode	Brother iPrint&Scan (Android)	Print from an Android device
Warm Up Time Print Languages	Less than 24 seconds from sleep mode PCL6, BR-Script3	Brother iPrint&Scan (iPad / iPhone / iPod)	Print from an iPad / iPhone / iPod Touch
· · · · · · · · · · · · · · · · · · ·	PDF Version 1.7, XPS Version 1.0	Brother iPrint&Scan (Windows [®] Phone)	Print from a smart phone running the Windows® Phone Operating System
Embedded Fonts (PCL) Embedded Fonts (Postscript)	73 scalable fonts, 12 bitmap fonts 66 scalable fonts	Brother Print&Scan (Windows [®] 8,10 & RT)	Print from a Windows [®] 8,10 or Windows RT Tablet
Embedded Barcodes (PCL)	*Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E,	Google Cloud Print 2.0	Print most common file types from any Google Cloud Print enabled application
	Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C),	Apple AirPrint	Print from and scan to most common file types from any AirPrint enabled application
	Code93, GS1Databar, MSI	Brother Print Service Plugin	Print from Android devices without a dedicated App
Printer Functions		Mopria	Print most common file types from Mopria supported Android devices
N-up Printing ³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)		
Poster Printing ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages		
Watermark Printing ⁴	Watermark your documents with predefined text or with	Fleet Management Tools	
watermark Filling	your own user-defined messages	Fleet Management Tools	
ID Printing ⁴	your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username)	Unattended Installer ⁴	Ability to centrally deploy and customise our drivers and software
	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex)		
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print)	Unattended Installer ⁴	and software Modular installers that can be distributed through Active
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print	Unattended Installer ⁴ MSI Installer ⁴	and software Modular installers that can be distributed through Active Directory®
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ⁴⁸⁵	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ⁴⁸⁵ Embedded Web Server	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ⁴⁸⁵ Embedded Web Server	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³ Print Text In Black ⁴	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ^{4&5} Embedded Web Server Driver Deployment Wizard ⁴ Software Brother iPrint&Scan	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment over your network Print from and check the machine status from windows
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³ Print Text In Black ⁴ Printer Driver	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when printed	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ⁴⁸⁵ Embedded Web Server Driver Deployment Wizard ⁴ Software	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment over your network
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³ Print Text In Black ⁴	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ^{4&5} Embedded Web Server Driver Deployment Wizard ⁴ Software Brother iPrint&Scan	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment over your network Print from and check the machine status from windows
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³ Print Text In Black ⁴ Printer Driver	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when printed Windows® 10 (32 & 64 bit editions), Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows® Server 2016 (32 & 64 bit editions)*, Windows® Server 2012, 2012R2 & 2008R2*,	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ^{4&5} Embedded Web Server Driver Deployment Wizard ⁴ Software Brother iPrint&Scan	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment over your network Print from and check the machine status from windows
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³ Print Text In Black ⁴ Printer Driver Windows [®]	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when printed Windows® 10 (32 & 64 bit editions), Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows® Server 2016 (32 & 64 bit editions) [*] , Windows® Server 2008 (32 & 64 bit editions) [*] , Windows® Server 2008 (32 & 64 bit editions) [*]	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ^{4&5} Embedded Web Server Driver Deployment Wizard ⁴ Software Brother iPrint&Scan	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment over your network Print from and check the machine status from windows
ID Printing ⁴ Manual 2-sided (duplex) Print ⁴ Booklet Printing ⁴ Print Profiles ³ Print Text In Black ⁴ Printer Driver Windows [®] Macintosh ⁵	Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print) Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when printed Windows® 10 (32 & 64 bit editions), Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows® Server 2012, 2012R2 & 2008R2*, Windows® Server 20208 (32 & 64 bit editions)* macOS v10.11.6, 10.12.x, 10.13.x	Unattended Installer ⁴ MSI Installer ⁴ BRAdmin Light ^{4&5} Embedded Web Server Driver Deployment Wizard ⁴ Software Brother iPrint&Scan	and software Modular installers that can be distributed through Active Directory® LAN/WAN management software Web based print management software embedded onto the device Easily create print drivers for hassle free deployment over your network Print from and check the machine status from windows

Network and Security	
Wired Network	Ethernet 10Base-T/100Base-TX
Wired Network Security	SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos
Wireless Network	IEEE 802.11b/g/n (Infrastructure Mode) IEEE 802.11g/n (Wi-Fi Direct)
Wireless Network Security	WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES) *WI-Fi Direct supports WPA2-PSK (AES) only.APOP, POP before SMTP, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP), SMMP v3 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos
Wi-Fi Direct™	Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)
Wireless Setup Support	Wi-Fi Protected Setup (WPS)
Wireless Applications	Vertical Pairing
IPv4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/ NetBIOS name resolution, DNS Resolver, mDNS, LLMINR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/ v3, ICMP, Web Services (Print), CIFS client, SNTP client
IPv6	NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMPv6, Web Services (Print), CIFS Client, SNTP Client
IP Filter	Restrict which network users can or cannot access the device over the network (IPv4 only)
E-mail Notifications	Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing
E-mail Reports	Receive usage reports on a regular basis via e-mail
Setting Lock	Secures access to the devices control panel by locking it
Secure Function Lock 3.0	Restrict access to individual or groups of users over a network. Can be used with PC User Login Names for up to 100 users
Secure Print	Protect print jobs with a 4 digit release code required at the device in order for them to be printed
Supplies and Accessories	
In-box Toner	Up to 1,000 pages ¹ C/M/Y/BK
Standard-Yield Toner	Up to 1,300 pages1 C/M/Y (TN-253)
High-Yield Toner	Up to 2,500 pages' BK (TN-253) Up to 2,300 pages' C/M/Y (TN-257)

Natural could be surfited

Dimensions and Weights	
Without Carton (WxDxH)	410 x 461x 252 mm -18kg
With Carton (WxDxH)	589 x 513 x 372 mm - 21.5kg
Duty Cycles	
Recommended Monthly	300 to 1,500 pages ⁸ monthly print volume
Environment	
Power Consumption	Printing - 390W, Ready - 75W, Quiet Mode - 270W, Sleep - 8.8W, Deep Sleep - 1.0W, Off - 0.04W
TEC Value	0.9 kWh/Week
Sound Pressure Level	Printing - 45dB(A) Ready - 33dB(A) Quiet Mode - 43dB(A)
Sound Power	Printing - 5.93B(A) Colour/Monochrome, Ready - 4.67B(A), Quiet Mode - 5.86B(A) Colour / 5.78B(A) Monochrome, Deep Sleep - Inaudible
Power Saving	This enables the printer to consume less energy when not in use
Toner Save Mode	This reduces the toner usage and helps to reduce the total cost of printer ownership
Energy Star	Yes
Eco Mode	Yes

1 Approx declared yield value in accordance with ISO/IEC 19798.

2 Calculated with 80g/m² paper.

3 Windows® & Mac® only.

4 Windows® only.

5 Optional download.

6 ISO print speed based on ISO/IEC 24734 (after first set of ISO test pages).7 Brother is the winner of PC Mag Readers' Choice Award for 9 years in a row and Business Choice Award for 5 years in a row.8 The recommended range of monthly printed pages to achieve the best possible

8 The recommended range of monthly printed pages to achieve the best possible performance and printer life. Printers are intended to handle occasional usage beyond the range with little or no effect. Consistently printing above the recommended print volume, however, may adversely affect the print quality or life of the machine. It is always best to choose a printer with an appropriate recommended print volume to allow for any anticipated increase in printing needs. * Windows[®] Server supports network printing only

All specifications correct at time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.





Drum Unit

Working with you for a better environment

Up to 18,000 pages1 (1 page / job) (DR-253CL)

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. www.brotherearth.com



youtube.com/user/BrotherAU/videos



linkedin.com/company/brother-international-australia/

